

1 N 5727	Itt,Hit	Si-Di	=1N5726: 50V	31a	DO-35			BAW 14, BAW 24...27
1 N 5728	USA,Phi,Sie	Z-Di	4,7V, 0,4W	31a	DO-35	Z-Diode 4,7V	31a	BZX55/..., BZX79/..., ZPD..., 1N5230...67,++
1 N 5729		Z-Di	=1N5728: 5,1V	31a	DO-35	Z-Diode 5,1V	31a	
1 N 5730		Z-Di	=1N5728: 5,6V	31a	DO-35	Z-Diode 5,6V	31a	
1 N 5731		Z-Di	=1N5728: 6,2V	31a	DO-35	Z-Diode 6,2V	31a	
1 N 5732		Z-Di	=1N5728: 6,8V	31a	DO-35	Z-Diode 6,8V	31a	
1 N 5733		Z-Di	=1N5728: 7,5V	31a	DO-35	Z-Diode 7,5V	31a	
1 N 5734		Z-Di	=1N5728: 8,2V	31a	DO-35	Z-Diode 8,2V	31a	
1 N 5735		Z-Di	=1N5728: 9,1V	31a	DO-35	Z-Diode 9,1V	31a	
1 N 5736		Z-Di	=1N5728: 10V	31a	DO-35	Z-Diode 10V	31a	
1 N 5737		Z-Di	=1N5728: 11V	31a	DO-35	Z-Diode 11V	31a	
1 N 5738		Z-Di	=1N5728: 12V	31a	DO-35	Z-Diode 12V	31a	
1 N 5739		Z-Di	=1N5728: 13V	31a	DO-35	Z-Diode 13V	31a	
1 N 5740		Z-Di	=1N5728: 15V	31a	DO-35	Z-Diode 15V	31a	
1 N 5741		Z-Di	=1N5728: 16V	31a	DO-35	Z-Diode 16V	31a	
1 N 5742		Z-Di	=1N5728: 18V	31a	DO-35	Z-Diode 18V	31a	
1 N 5743		Z-Di	=1N5728: 20V	31a	DO-35	Z-Diode 20V	31a	
1 N 5744		Z-Di	=1N5728: 22V	31a	DO-35	Z-Diode 22V	31a	
1 N 5745		Z-Di	=1N5728: 24V	31a	DO-35	Z-Diode 24V	31a	
1 N 5746		Z-Di	=1N5728: 27V	31a	DO-35	Z-Diode 27V	31a	
1 N 5747		Z-Di	=1N5728: 30V	31a	DO-35	Z-Diode 30V	31a	
1 N 5748		Z-Di	=1N5728: 33V	31a	DO-35	Z-Diode 33V	31a	
1 N 5749		Z-Di	=1N5728: 36V	31a	DO-35	Z-Diode 36V	31a	
1 N 5750		Z-Di	=1N5728: 39V	31a	DO-35	Z-Diode 39V	31a	
1 N 5751		Z-Di	=1N5728: 43V	31a	DO-35	Z-Diode 43V	31a	
1 N 5752		Z-Di	=1N5728: 47V	31a	DO-35	Z-Diode 47V	31a	
1 N 5753		Z-Di	=1N5728: 51V	31a	DO-35	Z-Diode 51V	31a	
1 N 5754		Z-Di	=1N5728: 56V	31a	DO-35	Z-Diode 56V	31a	
1 N 5755		Z-Di	=1N5728: 62V	31a	DO-35	Z-Diode 62V	31a	
1 N 5756		Z-Di	=1N5728: 68V	31a	DO-35	Z-Diode 68V	31a	
1 N 5757		Z-Di	=1N5728: 75V	31a	DO-35	Z-Diode 75V	31a	
1 N 5728A...5757A		Z-Di	=1N5728...5757: 5%	31a	DO-35			
1 N 5728B...5757B		Z-Di	=1N5728...5757: 2%	31a	DO-35			
1 N 5728C...5757C		Z-Di	=1N5728...5757: 1%	31a	DO-35			
1 N 5758	Mot	Diac	Ub=16...24V, Ib<0,1mA, Itsm=2A	71	TO-92			
1 N 5758 A	Mot	Diac	Ub=18...22V, Ib<0,025mA, Itsm=2A	71	TO-92			
1 N 5759	Mot	Diac	Ub=20...28V, Ib<0,1mA, Itsm=2A	71	TO-92			
1 N 5759 A	Mot	Diac	Ub=22...26V, Ib<0,025mA, Itsm=2A	71	TO-92			
1 N 5760	Mot	Diac	Ub=24...32V, Ib<0,1mA, Itsm=2A	71	TO-92			N 413L, D 3202U
1 N 5760 A	Mot	Diac	Ub=26...30V, Ib<0,025mA, Itsm=2A	71	TO-92			(N 413L, D 3202U)?
1 N 5761	Mot	Diac	Ub=28...36V, Ib<0,1mA, Itsm=2A	71	TO-92	BR 100	31	N 413M, BR 100, D 3202Y, D 0201YR
1 N 5761 A	Mot	Diac	Ub=30...34V, Ib<0,025mA, Itsm=2A	71	TO-92	(BR 100)?	31	(N 413M, BR 100, D 3202Y, D 0201YR)?
1 N 5762	Mot	Diac	Ub=32...40V, Ib<0,1mA, Itsm=2A	71	TO-92			N 413N, D 3202U
1 N 5762 A	Mot	Diac	Ub=34...38V, Ib<0,025mA, Itsm=2A	71	TO-92			(N 413N, D 3202U)?
1 N 5763	Del	Si-Di	P Fr, 26V, 300A(Tc=100°), Uf<1,2V(300A)					
1 N 5764	Miv	GaAs-Di	UHF, Ku-Band Mx	Koax	DO-37			
1 N 5766	SoI	Si-Di	FRr, 110V, Uf<1,7V(30A), <400ns	32a	DO-5			1N4525...4530
1 N 5767	Uni	Si-Di	Uni, 100V	31a	DO-34			BA 147/100, BA 188...190, 1N5606...09, ++
1 N 5768	Fch	Si-Di	8-Di Logik-Gatter/Logic Gate, 60V, 0,3A, <20ns	10-FLP	TO-89			
1 N 5770	Fch	Si-Di	8-Di Logik-Gatter/Logic Gate, 60V, 0,3A, <20ns	10-FLP	TO-89			
1 N 5772	Fch	Si-Di	=1N5768: 16 Di	10-FLP	TO-89			
1 N 5774	Fch	Si-Di	=1N5768: 16 Di	14-FLP	TO-86			
1 N 5779	Mot	Trigger-Di	=1N5158: Ub=11...13V	31a	DO-7			
1 N 5780	Mot	Trigger-Di	=1N5158: Ub=12...14V	31a	DO-7			
1 N 5781	Mot	Trigger-Di	=1N5158: Ub=13...15V	31a	DO-7			
1 N 5782	Mot	Trigger-Di	=1N5158: Ub=8...10V, Ib<0,1mA, Ih=10...50mA	31a	DO-7			
1 N 5783	Mot	Trigger-Di	=1N5158: Ub=9...11V, Ib<0,1mA, Ih=10...50mA	31a	DO-7			
1 N 5784	Mot	Trigger-Di	=1N5158: Ub=10...12V, Ib<0,1mA, Ih=10...50mA	31a	DO-7			
1 N 5785	Mot	Trigger-Di	=1N5158: Ub=11...13V, Ib<0,1mA, Ih=10...50mA	31a	DO-7			
1 N 5786	Mot	Trigger-Di	=1N5158: Ub=12...14V, Ib<0,1mA, Ih=10...50mA	31a	DO-7			
1 N 5787	Mot	Trigger-Di	=1N5158: Ub=13...15V, Ib<0,1mA, Ih=10...50mA	31a	DO-7			
1 N 5788	Mot	Trigger-Di	=1N5158: Ub=8...10V, Ib<0,1mA, Ih=0,1...2mA	31a	DO-7			
1 N 5789	Mot	Trigger-Di	=1N5158: Ub=9...11V, Ib<0,1mA, Ih=0,1...2mA	31a	DO-7			
1 N 5790	Mot	Trigger-Di	=1N5158: Ub=10...12V, Ib<0,1mA, Ih=0,1...2mA	31a	DO-7			
1 N 5791	Mot	Trigger-Di	=1N5158: Ub=11...13V, Ib<0,1mA, Ih=0,1...2mA	31a	DO-7			
1 N 5792	Mot	Trigger-Di	=1N5158: Ub=12...14V, Ib<0,1mA, Ih=0,1...2mA	31a	DO-7			
1 N 5793	Mot	Trigger-Di	=1N5158: Ub=13...15V, Ib<0,1mA, Ih=0,1...2mA	31a	DO-7			
1 N 5794	Fch	Si-Di	Rr, 50V, 1A, Uf<0,98V(1A, 75°)	31a	SOD-51			BY 126...127, BY 133...135, 1N4001...07, ++
1 N 5795		Si-Di	=1N5794: 100V	31a	SOD-51			BY 126...127, BY 133...135, 1N4002...07, ++
1 N 5796		Si-Di	=1N5794: 200V	31a	SOD-51			BY 126...127, BY 133...134, 1N4003...07, ++
1 N 5797		Si-Di	=1N5794: 400V	31a	SOD-51			BY 126...127, BY 133...134, 1N4004...07, ++
1 N 5798		Si-Di	=1N5794: 600V	31a	SOD-51			BY 126...127, BY 133...134, 1N4005...07, ++
1 N 5799		Si-Di	=1N5794: 800V	31a	SOD-51			BY 127, BY 133, BY 227, 1N4006...07, ++
1 N 5800		Si-Di	=1N5794: 1000V	31a	SOD-51			BY 127, BY 133, BY 227, 1N4007, ++
1 N 5802	USA,Gie	Si-Di	FRr, 50V, 2,5A, Uf<0,875V(1A), <25ns	31a	SOD-17	BYV 28/200	31a	BYV 28/50, EGP 30A, FE 3A
1 N 5803		Si-Di	=1N5802: 75V	31a	SOD-17	BYV 28/200	31a	BYV 28/100, EGP 30B, FE 3B
1 N 5804		Si-Di	=1N5802: 100V	31a	SOD-17	BYV 28/200	31a	BYV 28/100, EGP 30B, FE 3B
1 N 5805		Si-Di	=1N5802: 125V	31a	SOD-17	BYV 28/200	31a	BYV 28/150, EGP 30C, FE 3C
1 N 5806		Si-Di	=1N5802: 150V	31a	SOD-17	BYV 28/200	31a	BYV 28/150, EGP 30C, FE 3C
1 N 5807	USA,Gie	Si-Di	FRr, 50V, 6A, Uf<0,875V(4A), <30ns	31a	SOD-51			BYV 61...63, FE 6A
1 N 5808		Si-Di	=1N5807: 75V	31a	SOD-51			BYV 62...63, FE 6B
1 N 5809		Si-Di	=1N5807: 100V	31a	SOD-51			BYV 62...63, FE 6B
1 N 5810		Si-Di	=1N5807: 125V	31a	SOD-51			BYV 63, FE 6C
1 N 5811		Si-Di	=1N5807: 150V	31a	SOD-51			BYV 63, FE 6C
1 N 5812	USA,Gie	Si-Di	P FRr, 50V, 20A, Uf<0,9V(10A), <25ns	32a	DO-4			BYW 77/50
1 N 5813		Si-Di	=1N5812: 75V	32a	DO-4			BYW 77/100
1 N 5814		Si-Di	=1N5812: 100V	32a	DO-4			BYW 77/100
1 N 5815		Si-Di	=1N5812: 125V	32a	DO-4			BYW 77/150
1 N 5816		Si-Di	=1N5812: 150V	32a	DO-4			BYW 77/150
1 N 5817	Gie,Mot,Phi Itt,Tho	Si-Di	Schottky Rr, 20V, 1A, Uf<0,45V(1A)	31a	DO-15	1N5822	31	BYS 21, BYV 10-20, SB 120
1 N 5818		Si-Di	=1N5817: 30V, Uf<0,55V(1A)	31a	DO-15, -41	1N5822	31a	BYS 21, BYV 10-30, SB 130
1 N 5819		Si-Di	=1N5817: 40V, Uf<0,6V(1A)	31a	DO-15, -41	1N5822	31a	BYS 21, BYV 10-40, SB 140